



## Certificate G83/1-1

### Engineering Recommendation

Manufacturer	<b>SMA Solar Technology AG</b>
Address	Sonnenallee 1
Postal code, place	34266 Niestetal
Country	Germany

Test house details	<b>SMA Solar Technology AG</b>
--------------------	--------------------------------

Type reference	Max. AC power	Nominal AC power
SB 3000TL-21/WB 3000TL-21	3,000 VA	3,000 VA
SB 3600TL-21/WB 3600TL-21	3,680 VA	3,680 VA
SB 4000TL-21/WB 4000TL-21	4,000 VA	4,000 VA
SB 5000TL-21/WB 5000TL-21	5,000 VA	4,600 VA

The results of the G83/1-1 tests are summarized in this certificate. SMA declares that all devices (with G83 setting) that are shipped to the UK comply with the requirements defined in engineering recommendation G83/1-1. These settings cannot be changed by an installer, user or by any other person without the use of a tool (password protected). The complete documentation can be viewed at SMA (headquarters) after prior announcement.

**SMA Solar Technology AG**  
Niestetal, 2012-10-10

ppa. Frank Greizer  
(Vice President MP T PD)

# Test Results

## Power Quality

Harmonic current emissions as per BS EN 61000-3-2										
Harmonic	2 <sup>nd</sup>	3 <sup>rd</sup>	5 <sup>th</sup>	7 <sup>th</sup>	9 <sup>th</sup>	11 <sup>th</sup>	13 <sup>th</sup>	15 <sup>th</sup> ... 39 <sup>th</sup>		
BS EN 61000-3-2 Limit [A]	1.08	2.30	1.14	0.77	0.40	0.33	0.21	0.15 x (15/n)		
Test value [A] (at rated power)	SB 3000TL-21	0.01	1.13	0.04	0.04	0.04	0.02	0.02	< limit BS EN 61000-3-2 A	
	WB 3000TL-21									
	SB 3600TL-21	0.01	1.17	0.05	0.04	0.03	0.02	0.02		
	WB 3600TL-21									
	SB 4000TL-21	0.02	0.19	0.04	0.04	0.03	0.02	0.02		
	WB 4000TL-21									
	SB 5000TL-21	0.01	0.24	0.04	0.04	0.03	0.03	0.02		
	WB 5000TL-21									

Voltage fluctuations and flicker				
	Starting	Stopping	Running (at rated power)	
BS EN 61000-3-3 Limit	4%	4%	$P_{st} = 1.0$	$P_{lt} = 0.65$
Test value	0.00%	0.00%	0.27	0.20

	DC injection		
G83/1-1 Limit	20 mA		
Test level (% of rated power)	10%	55%	100%
Test value	< 10 mA	< 14 mA	< 14 mA

	Power factor		
G83/1-1 Limit	0.95 lag - 0.95 lead at three voltage levels at $P_{rated}$		
Test level (AC voltage)	211 V	230 V	259 V
Test value (at rated power)	> 0.99	> 0.99	> 0.99

# Test Results

## Grid Monitoring and Reconnection Time

Undervoltage/overvoltage				
	Undervoltage switch off		Overvoltage switch off	
Parameter	Voltage	Time	Voltage	Time
G83/1-1 Limit	207 V	5 s	264 V	5 s
Actual setting	207 V	5 s	264 V	5 s
Trip value	209 V	4.97 s	264 V	4.97 s

Under/over frequency				
	Under frequency switch off		Over frequency switch off	
Parameter	Frequency	Time	Frequency	Time
G83/1-1 Limit	47 Hz	5 s	50.5 Hz	5 s
Actual setting	47 Hz	5 s	50.5 Hz	5 s
Trip value	47 Hz	4.5 s	50.5 Hz	4.49 s

Loss of mains tests (method used: frequency shift)				
Test level (% of rated power)	10%	55%	100%	
G83/1-1 Limit	5 s	5 s	5 s	
Actual setting	-	-	-	
Trip value	< 2.5 s	< 2.5 s	< 2.5 s	

Reconnection times			
Test level (% of rated power)	Undervoltage/overvoltage	Under/over frequency	Loss of mains
Minimum value	180 s	180 s	180 s
Actual setting	180 s	180 s	180 s
Recorded value	> 184 s	> 184 s	> 184 s

### Fault Level Contribution

As SSEGs (small-scale embedded generators) for PV or wind turbine systems are inverter-connected, they are deemed to automatically comply with regulations and no further tests are required.

### Self Monitoring – Solid State Switching

Not applicable as electro-mechanical relays used.