



Device for Closing Dead Zones with SMA Bluetooth®
Wireless Technology

SMA BLUETOOTH REPEATER OUTDOOR

Installation Manual



Table of Contents

1	Information on this Document	5
2	Safety	7
2.1	Intended Use	7
2.2	Qualification of Skilled Persons	8
2.3	Safety Precautions	8
3	Scope of Delivery	9
3.1	Order Option Top-Hat Rail Power Supply Unit	9
3.2	Order Option Power Module	10
3.3	Identifying the SMA <i>Bluetooth</i> Repeater Outdoor	10
4	Product Description	11
4.1	Range of Usage	11
4.2	Functions	11
4.3	Device Overview	12
5	Assembly	15
5.1	Selecting the Mounting Location	15
5.2	Mounting the <i>Bluetooth</i> Repeater Outdoor on the Wall	18
6	Electrical Connection	19
6.1	Connecting the <i>Bluetooth</i> Repeater Outdoor with Top-Hat Rail Power Supply Unit to the Voltage Supply	19
6.2	Connecting the <i>Bluetooth</i> Repeater Outdoor to the Voltage Supply	21
7	Settings	23
7.1	Setting the MODE	23
7.2	Setting the NetID	23
8	Maintenance and Care	25
9	Decommissioning	26
9.1	Detaching the <i>Bluetooth</i> Repeater From The Wall	26
9.2	Packing the <i>Bluetooth</i> Repeater Outdoor	26
9.3	Disposing of the SMA <i>Bluetooth</i> Repeater	26

10 Troubleshooting 27

 10.1 Voltage Supply 27

 10.1.1 LED RDY..... 27

 10.1.2 LEDs of the Top-Hat Rail Power Supply Unit 29

 10.2 Connection Quality 30

11 Technical Data 32

12 Contact 34

1 Information on this Document

Validity

This document is valid for the following device types as of hardware version A1 and firmware version V 1.07.R:

- BTREP-OUT.GR1
- BTREP-OUT.GR2

Target Group

This document is for skilled persons. Only qualified personnel with the appropriate skills are allowed to perform the tasks described in this manual (see Section 2.2 "Qualification of Skilled Persons", page 8).

Additional Information

Links to additional information can be found at www.SMA-Solar.com:

Document title	Document type
SMA Bluetooth® Wireless Technology	Technical description
SMA Bluetooth® Wireless Technology in Practice	Technical information

Symbols

Symbol	Explanation
 DANGER	Indicates a hazardous situation which, if not avoided, will result in death or serious injury
 WARNING	Indicates a hazardous situation which, if not avoided, could result in death or serious injury
 CAUTION	Indicates a hazardous situation which, if not avoided, could result in minor or moderate injury
NOTICE	Indicates a situation which, if not avoided, could result in property damage
	Information that is important for a specific topic or goal, but is not safety-relevant
	Indicates an essential requirement for achieving a specific goal
	Desired result
	A problem that might occur

Typographies

Typography	Usage	Example
bold	• Display messages • Elements of a user interface • Connections • Elements to be selected • Elements to be entered	• The value can be read from the Energy field. • Select Settings. • Enter the value 10 in the Minutes field.
>	• Connects several elements that are to be selected	• Select Settings > Date.
[Button/Key]	• Button or key to be selected or pressed	• Select [Next].

Nomenclature

Complete designation	Designation in this document
PV plant	Plant
Small wind turbine system	Plant
SMA <i>Bluetooth</i> Piggy-Back	<i>Bluetooth</i> Piggy-Back
SMA <i>Bluetooth</i> Piggy-Back Plus	<i>Bluetooth</i> Piggy-Back Plus
SMA <i>Bluetooth</i> Repeater Outdoor	<i>Bluetooth</i> Repeater Outdoor
Sunny Beam with <i>Bluetooth</i> ® Wireless Technology	Sunny Beam with <i>Bluetooth</i>

Abbreviations

Abbreviation	Designation	Explanation
AC	Alternating Current	–
DC	Direct Current	–
LED	Light-Emitting Diode	–
WLAN	Wireless Local Area Network	–

2 Safety

2.1 Intended Use

The *Bluetooth Repeater Outdoor* is used in outdoor installations to close dead zones under unfavourable installation conditions between SMA Solar Technology AG devices by means of *Bluetooth* or to improve poor wireless connections.

The *Bluetooth Repeater Outdoor* is intended for private and industrial use. Use the *Bluetooth Repeater Outdoor* in outdoor installations.

The SMA *Bluetooth Repeater Outdoor* may only be used with supported products:

For safety reasons, it is not permitted to modify the product or install components that are not explicitly recommended or distributed by SMA Solar Technology AG for this product.

The enclosed documentation is an integral part of this product.

- Read and observe the documentation.
- Keep the documentation in a convenient place for future reference.

Only use the SMA *Bluetooth Repeater Outdoor* in accordance with the information provided in the enclosed documentation. Any other use may result in personal injury or property damage.

Supported Products

The SMA *Bluetooth Repeater Outdoor* may only be used with the following SMA Solar Technology AG products:

- All SMA communication products with *Bluetooth*
- All inverters with SMA *Bluetooth Piggy-Back* upgrade. A list of supported inverters can be found in the SMA *Bluetooth Piggy-Back* installation manual.
- All inverters with SMA *Bluetooth Piggy-Back Plus* upgrade. A list of supported inverters can be found in the SMA *Bluetooth Piggy-Back* installation manual.
- SMA PV inverters with integrated *Bluetooth*:
 - SB (Sunny Boy) 3000TL-20/SB 4000TL-20/SB 5000TL-20: from software package 2.06
 - SB 3000TL-21/SB 4000TL-21/SB 5000TL-21
 - SB 2000HF-30/SB 2500HF-30/SB 3000HF-30
 - STP (Sunny Tripower) 10000TL-10/STP 12000TL-10/STP 15000TL-10/STP 17000TL-10
- SMA wind power inverters with integrated *Bluetooth*:
 - WB (Windy Boy) 3600TL-20/WB5000TL-20
 - WB 2000HF/WB 2500HF/WB 3000HF

2.2 Qualification of Skilled Persons

The work described in this document must be performed by skilled persons only. Skilled persons must have the following qualifications:

- Training in the installation and commissioning of electrical devices and plants
- Knowledge of how to deal with the dangers and risks associated with the installation and operation of electrical devices and plants
- Knowledge of all applicable standards and directives
- Knowledge of how an inverter works and is operated
- Knowledge of and adherence to this document and all safety precautions

2.3 Safety Precautions

Electric Shock

Lethal voltages are present in the conductive parts of the inverter.

- Prior to performing any work on the inverter, disconnect the inverter from any voltage sources on the AC and DC sides (see inverter installation manual). Observe the waiting time to allow the capacitors to discharge.

Burn Hazards

Some parts of the inverter enclosure can get hot during operation.

- During operation, touch the inverter on the enclosure lid only.

Environmental Influences

When closed, the *Bluetooth Repeater Outdoor* has the degree of protection IP54.

The *Bluetooth Repeater Outdoor* is thus protected against dust intrusion and water penetration. Dust intrusion and water penetration can damage the *Bluetooth Repeater Outdoor*.

- When the enclosure of the *Bluetooth Repeater Outdoor* is not closed, protect the *Bluetooth Repeater Outdoor* against dust intrusion and water penetration.
- Close the enclosure of the *Bluetooth Repeater Outdoor* again after performing any work on the *Bluetooth Repeater Outdoor*.

Electrostatic Discharge

By touching electronic components, you can damage or even destroy the inverter or the *Bluetooth Repeater Outdoor* through electrostatic discharge (ESD).

- Earth yourself before touching any components of the inverter or the *Bluetooth Repeater Outdoor*.

3 Scope of Delivery

3.1 Order Option Top-Hat Rail Power Supply Unit

Check the scope of delivery for completeness and any externally visible damage. Contact your specialist dealer if the scope of delivery is incomplete or damaged.




Figure 1: Components included in the scope of delivery with order option top-hat rail power supply unit

Item	Quantity	Description
A	1	Bluetooth Repeater Outdoor (device type „BTREP-OUT.GR1“), pre-assembled
B	4	Screw
C	4	Wall plug

3.2 Order Option Power Module

Check the scope of delivery for completeness and any externally visible damage. Contact your specialist dealer if the scope of delivery is incomplete or damaged.




Figure 2: Components included in the scope of delivery with order option Power Module

Item	Quantity	Description
A	1	Bluetooth Repeater Outdoor (device type „BTREP-OUT.GR2“), pre-assembled
B	1	Power Module for the voltage supply (for scope of delivery see the installation manual of the Power Module)
C	4	Screw
D	4	Wall plug

3.3 Identifying the SMA Bluetooth Repeater Outdoor

You can identify the SMA Bluetooth Repeater Outdoor by means of the type label. The type label is on the right-hand side of the SMA Bluetooth Repeater Outdoor.

4 Product Description

4.1 Range of Usage




Figure 3: Use of the *Bluetooth Repeater Outdoor* (example)

The *Bluetooth Repeater* is used in outdoor installations to close dead zones under unfavourable installation conditions between SMA Solar Technology AG devices with *Bluetooth* or to improve poor wireless connections.

Item	Description
A	Inverter with <i>Bluetooth</i>
B	<i>Bluetooth Repeater Outdoor</i>
C	Communication device with <i>Bluetooth</i>

4.2 Functions

- Connection to SMA devices with *Bluetooth* via *Bluetooth Class 1*
- Maximum range of up to 100 m in free-field conditions with direct visual contact
- Can be used outdoors, thanks to weatherproof enclosure

4.3 Device Overview




Figure 4: Overview of the enclosure elements (with enclosure lid (left-hand) and enclosure bottom (right-hand))

Item	Description
A	Seal
B	Enclosure lid screw
C	Top-hat rail power supply unit*
D	Feed-through terminal for the connection to the voltage supply
E	Enclosure opening for voltage supply
F	Opening with self-adhesive membrane for pressure equalisation
G	Screw seal with screwable seal insert, by means of which there is access to the rotary switches MODE and NetID
H	Bluetooth Repeater

* only included in order option top-hat rail power supply unit

i Do not damage or remove the self-adhesive membrane

The self-adhesive membrane is a pressure membrane balance element, e. g. for heat generation in the inside of the enclosure, and ensures the tightness of the enclosure in accordance with the degree of protection IP54* .

* according to IEC 60529




Figure 5: Overview of the device elements on the *Bluetooth Repeater Outdoor*

Item	Description	Colour	Explanation
A	–	–	Terminal DC source (top-hat rail power supply unit or Power Modul)
B	RDY	Green	LED for voltage supply
C	MODE	–	Rotary switch for configuring the MODE
D	NetID	–	Rotary switch for configuring the NetID
E	–	Blue	<i>Bluetooth</i> LED
F	–	Yellow	<i>Bluetooth</i> LEDs




Figure 6: Overview of the LEDs of the top-hat rail power supply unit

Item	Description	Colour	Explanation
A	DC LO	Yellow	LED for voltage supply
B	DC OK	Green	LED for voltage supply



Figure 7: Overview of the terminals on the feed-through terminal

Item	Description
A	Terminal 1 for the connection of the voltage supply cable
B	Terminal 2 for the connection of the voltage supply cable

5 Assembly

5.1 Selecting the Mounting Location

Requirements for the mounting location:

- ☐ If the top-hat rail power supply is used, the mounting location must be in the vicinity of a socket-outlet in the interior area.
- ☐ The mounting location must be protected against dust, moisture and corrosive substances.

Observe the maximum cable length:

- ☐ If a Power Module is used, observe the maximum cable length of 10 m for the voltage supply cable.

Observe minimum clearances:




Figure 8: Minimum clearances to be observed

- Observe the minimum clearance to walls and other devices or objects.
- Observe the minimum clearance of 1 m to devices using the 2.4 GHz frequency band, e. g. WLAN devices or microwave ovens. This is to prevent any reduction in connection quality or data transmission speed.

Determining the Mounting Location

Determine the mounting location by varying the distance between the *Bluetooth Repeater Outdoor* and devices with a critical connection signal until all devices display at least a "good" signal.

Requirements:

- ☐ The rotary switch **MODE** is at position **0** (see Section 7.1 "Setting the MODE", page 23).
- ☐ The rotary switch **NetID** is set to the NetID of the plant (see Section 7.2 "Setting the NetID", page 23).

DANGER

Danger to life due to electric shock when opening the inverter

Lethal voltages are present in the conductive parts of the inverter.

- Prior to performing any work on the inverter, disconnect the inverter from any voltage sources on the AC and DC sides (see inverter installation manual). Observe the waiting time to allow the capacitors to discharge.

1. Decommission the plant (see the manual of the inverter and of the communication product). Thus, you ensure that the *Bluetooth Repeater Outdoor* is integrated into the *SMA Bluetooth* network at the point where the dead zone is, thus improving the *Bluetooth* connection at that point.
2. Position the *Bluetooth Repeater Outdoor* half way between the devices with critical connection quality.
3. Connect the voltage supply (see Section 6 "Electrical Connection", page 19).
4. Recommission the plant (see the installation manual of the inverter and of the communication product).
5. Repeat the plant search with the communication device (see the communication product manual, e.g. Sunny Beam with *Bluetooth*, Sunny Explorer).

6. Check that the connection quality for all devices is at least "good". During this procedure, all devices must be in their usual positions (e.g., the Sunny Beam with *Bluetooth* must not be held directly in front of the *Bluetooth Repeater Outdoor*):

Product	Good connection quality
<i>Bluetooth Repeater Outdoor</i>	One blue and two yellow LEDs are lit
Sunny Boy of the type SB x000TL-2x and SB xx00HF-30, Sunny Tripower of the type STP xx000TL-10	At least two rings are shown in the inverter display 
Other types of SMA inverters with <i>Bluetooth Piggy-Back</i> or <i>Bluetooth Piggy-Back Plus</i>	Use the communication product to check whether the connection signal is improved by using the <i>Bluetooth Repeater Outdoor</i> (see manual of the communication product)
Communication product	See manual of the communication product


- ☒ The connection quality displayed is at least "good" for all devices. Mount the *Bluetooth Repeater Outdoor* there at this location.
- ☒ The connection quality displayed is not at least "good" for all devices?
 - Move the *Bluetooth Repeater Outdoor* to another position and check the connection signals again.
 - If necessary, install additional SMA *Bluetooth Repeater Outdoor* devices.

5.2 Mounting the *Bluetooth Repeater Outdoor* on the Wall


Requirement:

- ☐ *Bluetooth Repeater Outdoor* must be disconnected.

1. Loosen the screws of the enclosure lid and remove the lid.
2. Drill holes through the indentation in the enclosure edges. Use a drill bit (4 mm) for this purpose.




3. Mark the holes with the help of the pre-drilled holes in the enclosure on the wall.



4. Drill the holes at the marked positions.

5. Attach the *Bluetooth Repeater Outdoor* to the wall using wall plugs and screws
6. Remove the seals from the inside of the enclosure lid and press them onto screws.



7. Reattach the enclosure lid using the enclosure lid screws.

6 Electrical Connection

6.1 Connecting the *Bluetooth* Repeater Outdoor with Top-Hat Rail Power Supply Unit to the Voltage Supply

DANGER

Danger to life due to electric shock in the event of missing separators and missing fuses on the AC cable

- The AC cable used for the connection must have a separator.
 - In the case of an alternating current supply by means of an IT system the separator must have two poles in accordance with IEC 60364-1.
- The separator must be easily accessible.
- If the separator is a plug-connection, the socket-outlet must be situated in close proximity to the *Bluetooth* Repeater Outdoor.
- The AC cable used for the connection must be equipped with a fuse (16 A for Europe and 20 A for the US and Canada).

DANGER

Danger to life due to electric shock in the event of mixing up the *Bluetooth* Repeater Outdoor

Only the *Bluetooth* Repeater Outdoor of the device type „BTREP-OUT.GR1“ is allowed to be connected via the top-hat rail power supply unit to the alternating current grid.


- Ensure that the *Bluetooth* Repeater Outdoor is of device type „BTREP-OUT.GR1“ before connecting it to the alternating current grid. To do so, check the type label on the *Bluetooth* Repeater Outdoor (see Section 3.3 "Identifying the SMA *Bluetooth* Repeater Outdoor", page 10).

Requirements for the connection cable:


- ☐ Number of insulated wires: 2
- ☐ Cable cross-section: 1 mm² ... 2.5 mm²
- ☐ External diameter: 5 mm ... 10 mm
- ☐ Cable must be suitable for outdoor installations.
- ☐ Cable must be UV resistant.
- ☐ If a grid connection plug is used in outdoor installations: Grid connection plug must be suitable for outdoor installations.

1. Loosen the screws of the enclosure lid and remove the lid.
2. Unscrew the nut from the lower left corner of the cable gland and push out the filler-plug.
3. Preparing the cable:

- Remove 40 mm of the cable sheath from the side of the *Bluetooth Repeater Outdoor*.
- Shorten unused insulated wires flush with the cable sheath.
- Strip approx. 10 mm off the wires.




4. Insert the cable into the enclosure through the nut and the cable gland.




5. Connecting the cable to the feed-through terminal in the enclosure:

- Push the terminal 1 and terminal 2 of the feed-through terminal open using a screwdriver (2.5 mm).
- Connect the conductor to terminal 1 and the insulator to terminal 2.



6. Separate the AC grid connection point from the alternating current grid using the separator. Thus you ensure that there is no voltage present at the AC grid connection point.
7. Connect the *Bluetooth Repeater Outdoor* to the voltage supply.
 - Plug the grid connection plug into the socket-outlet, if a grid connection plug is used.
 - If no grid connection plug is used, connect the other end of the cable to the voltage supply as desired, e.g. via a cable junction box.
8. Connect the AC grid connection point to the AC grid using the separator.
 - ☑ LED **DC OK** of the top-hat rail power supply unit and LED **RDY** of the *Bluetooth Repeater Outdoor* are glowing green
 - ✗ LED **DC LO** of the top-hat rail power supply unit or LED **RDY** are not in operation or are glowing yellow?
 - Rectify the fault (see Section 10.1 "Voltage Supply", page 27).

9. Check whether the cable gland seal is correctly in place. The seal must not protrude over the cable gland.



10. Hand-tighten the nut to the cable gland. Tighten the nut with a torque of 0.8 Nm thus securing the cable.
11. Reattach the enclosure lid using the enclosure lid screws.

6.2 Connecting the *Bluetooth Repeater Outdoor* to the Voltage Supply

⚠ DANGER

Danger to life due to electric shock when opening the inverter

Lethal voltages are present in the conductive parts of the inverter.


- Prior to performing any work on the inverter, disconnect the inverter from any voltage sources on the AC and DC sides (see inverter installation manual). Observe the waiting time to allow the capacitors to discharge.

Requirement:


- ☐ The Power Module is installed in the inverter (see Power Module installation manual).

1. Loosen the enclosure lid screws and remove the enclosure lid from the *Bluetooth Repeater Outdoor*.
2. Unscrew the nut from the lower left corner of the cable gland of the enclosure and push the filler-plug out of the nut.
3. Preparing the cable:


- Remove 40 mm of the cable sheath from the side of the *Bluetooth Repeater Outdoor*.
- Shorten unused insulated wires flush with the cable sheath.
- Strip approx. 10 mm off the wires.



4. Insert the cable into the enclosure through the nut and the cable gland.



5. Connecting the cable to the feed-through terminal in the inside of the enclosure:
 - Push the terminal **1** and terminal **2** of the feed-through terminal open using a screwdriver (2.5 mm).
 - Connect the wires of the cable to terminal **1** and terminal **2**. The polarity is arbitrary.




6. Recommission the inverter with installed Power Module (see inverter manual).

☑ LED **RDY** is glowing green.

✗ The LED **RDY** is off or flashing?

- Rectify the fault (see Section 10.1 "Voltage Supply", page 27).

7. Check that the cable gland seal is correctly in place. The seal must not protrude over the cable gland.




8. Hand-tighten the nut to the cable gland. Tighten the nut with a torque of 0.8 Nm thus securing the cable.
9. Reattach the enclosure lid using the enclosure lid screws.

7 Settings

7.1 Setting the MODE

The **MODE** rotary switch is set to the position **0** for delivery. Other positions are not permitted and are intended for SMA Service only.

- If the **MODE** rotary switch is not positioned correctly, set the correct position:
 - Remove the seal insert of the screw seal from the top of the *Bluetooth Repeater Outdoor* using a screwdriver (2.5 mm). Thus you can see the **MODE** rotary switch in the inside of the enclosure and reach it using the screwdriver (2.5 mm).
 - Turn the arrow of the **MODE** rotary switch to the correct position using a screwdriver (2.5 mm).
 - Insert the seal insert of the screw seal and tighten it using a screwdriver (2.5 mm). This ensures the degree of protection IP54.



7.2 Setting the NetID

The NetID serves to distinguish PV plants with SMA *Bluetooth* operating in close proximity to one another. All devices in a PV plant must have the same NetID. You can set the SMA *Bluetooth Repeater Outdoor* to the **NetID** of your plant using the "NetID" rotary switch.

Assignment of the rotary switch positions*	
NetID	Function
0	<i>Bluetooth</i> is switched off.
1 (Default setting)	<i>Bluetooth</i> is switched on. The device can connect to a maximum of two communication products. The device cannot connect to other inverters or SMA <i>Bluetooth Repeaters</i> .
2 ... 9 and A ... F	<i>Bluetooth</i> is switched on. The device can interlink with all SMA <i>Bluetooth</i> products with the same NetID.

* See Section 10.2 for information on the status of the *Bluetooth* LEDs.

i NetID 1 is possible for plants with 1 inverter

You may leave the default NetID set to 1 in your inverter if your *Bluetooth* plant consists of the following products:


- A maximum of one inverter
- A maximum of one computer with *Bluetooth* and the Sunny Explorer software
- A maximum of one Sunny Beam of type BEAM-BT-1 1.GR1

or

- A maximum of one inverter
- A maximum of 2 Sunny Beams of type BEAM-BT-1 1.GR1

In all other cases you must determine a free NetID (see Sunny Explorer Help).

1. If you do not know the plant NetID, read off the NetID from one of the devices in the plant (see the manual of the device).
2. Remove the seal insert of the screw seal from the top of the enclosure of the *Bluetooth* Repeater Outdoor with a screwdriver (2.5 mm). Thus you can see the **NetID** rotary switch and the *Bluetooth* LEDs in the inside of the enclosure.



3. Use a screwdriver (2.5 mm) to turn the arrow of the **NetID** rotary switch to the plant NetID.
4. Insert the seal insert of the screw seal and tighten it using a screwdriver (2.5 mm). This ensures the degree of protection IP54.

8 Maintenance and Care

- Check the *Bluetooth Repeater Outdoor* regularly for external damage or soiling.
- If external damage to the *Bluetooth Repeater Outdoor* is severe enough to impair correct function, replace the *Bluetooth Repeater Outdoor*.
- If the *Bluetooth Repeater Outdoor* is soiled, clean the *Bluetooth Repeater Outdoor* using only a slightly damp cloth. Any cleaning agents used must be non-abrasive and non-corrosive.

9 Decommissioning

9.1 Detaching the *Bluetooth Repeater Outdoor*.

1. When connecting to the AC grid separate the *Bluetooth Repeater Outdoor* from the voltage supply using the separator and check that there is no voltage present in the cable. When a grid connection plug is used remove it from the socket-outlet.
2. Remove the cable gland of the Power Module for the connection to the Power Module (see installation manual of the Power Module).
3. Loosen the screws of the enclosure lid and remove the lid.
4. Remove the screws of the enclosure from the wall and take down the *Bluetooth Repeater Outdoor*.
5. Remove the cable from the feed-through terminal in the inside of the enclosure.
 - Push open terminal **1** and terminal **2** of the feed-through terminal using a screwdriver (2.5 mm)
 - Pull out the wires of the cable.
 - Remove the cable from the enclosure. To do this, unscrew the nut from the lower left corner of the cable gland of the enclosure and pull out the cable gland from the enclosure.
6. Reattach the enclosure lid using the enclosure lid screws.

9.2 Packing the *Bluetooth Repeater Outdoor*

- Pack the *Bluetooth Repeater Outdoor* using the original packaging or packaging that is suitable for the weight and size of the *Bluetooth Repeater Outdoor* (see Section 11 "Technical Data", page 32).

9.3 Disposing of the *SMA Bluetooth Repeater*

- Dispose of the *Bluetooth Repeater Outdoor* in accordance with the locally applicable disposal regulations for electronic waste.

or

Send the *Bluetooth Repeater Outdoor* back to SMA Solar Technology AG with shipping paid by sender. When doing so, label the packaging "ZUR ENTSORGUNG" ("FOR DISPOSAL").

10 Troubleshooting

10.1 Voltage Supply

10.1.1 LED RDY

The LED **RDY** is only visible when the enclosure lid is open.

- In order to open the enclosure lid loosen the four enclosure lid screws.

Status	Meaning	Measure
permanently glowing green	The supply voltage is good. <i>Bluetooth Repeater Outdoor</i> is in operation.	None
flashes green and all other LEDs are switched off.	Power supply is marginal. <i>Bluetooth Repeater Outdoor</i> is in operation.	If you are using the top-hat rail power supply unit: • Contact the SMA Service Line.
		If you are using the Power Module: • If you are using the cable included in the delivery: – Contact the SMA Service Line. • If you are using a different cable: – Improve the power supply via one of the following measures: – Shorten the cable. – Choose a larger cable cross-section.
flashes green and all other LEDs are flashing	The <i>Bluetooth Repeater Outdoor</i> firmware is defective.	• Contact the SMA Service Line.

Status	Meaning	Measure
off	No power supply or the power supply is too low. The <i>Bluetooth Repeater Outdoor</i> is not in operation.	If you are using the top-hat rail power supply unit: Check whether the socket-outlet is supplying voltage. - Do this, for example, by connecting a different device to the socket-outlet. If the socket-outlet is providing voltage, then either the top-hat rail power supply unit or the <i>Bluetooth Repeater Outdoor</i> is defective. - Contact the SMA Service Line.
		If you are using the Power Module: - If you are using the cable included in the delivery: - Contact the SMA Service Line. - If you are using a different cable: - Check the wiring. If the wiring is correct, either the Power Module or the <i>Bluetooth Repeater Outdoor</i> is defective. - Contact the SMA Service Line.

10.1.2 LEDs of the Top-Hat Rail Power Supply Unit

The LEDs of the top-hat rail power supply unit are only visible when the enclosure lid is opened.

- In order to open the enclosure lid loosen the four enclosure lid screws.

Status	Meaning	Measure
The LED DC OK is glowing green and the LED DC LO is switched off.	The supply voltage is good. <i>Bluetooth Repeater Outdoor</i> is in operation.	None
The LED DC OK is switched off and the LED DC LO is glowing yellow	The supply voltage is too low. The <i>Bluetooth Repeater Outdoor</i> is not in operation.	Check whether the socket-outlet is supplying voltage. • Do this, for example, by connecting a different device to the socket-outlet. If the socket-outlet is providing voltage, then either the top-hat rail power supply unit or the <i>Bluetooth Repeater Outdoor</i> is defective. - Contact the SMA Service Line.
Both LEDs are switched off.	No supply voltage The <i>Bluetooth Repeater Outdoor</i> is not in operation.	Check whether the socket-outlet is supplying voltage. • Do this, for example, by connecting a different device to the socket-outlet. If the socket-outlet is providing voltage, then either the top-hat rail power supply unit or the <i>Bluetooth Repeater Outdoor</i> is defective. - Contact the SMA Service Line.

10.2 Connection Quality

The *Bluetooth Repeater Outdoor* can only display the connection quality if it is integrated into an existing *SMA Bluetooth* network. The *SMA Bluetooth* network can only be established by a master*. Devices will always display the connection signal to the device from which the connection has been established.

Bluetooth LEDs			
Status		Meaning	Measure
blue LED	yellow LEDs		
 permanently lit	 3 LEDs are permanently lit	Connection quality very good	None
	 Two LEDs are permanently lit	Connection quality good	None
	 One LED is permanently lit	Connection quality is unreliable	- Change the position of the <i>Bluetooth Repeater Outdoor</i>. or - Install additional <i>Bluetooth Repeater Outdoor</i> devices.
	 Three LEDs off	Connection quality critical	

* "Master" is a network engineering term. In a network, a master is a device that for example requests other devices (slaves) to receive or send data. All communication products (e.g. Sunny Explorer, Sunny Beam with *Bluetooth*) are masters in an *SMA Bluetooth* network.

Bluetooth LEDs			
Status		Meaning	Measure
blue LED	yellow LEDs		
 off	 Three LEDs off	The Bluetooth Repeater Outdoor is not connected to the Bluetooth network:	• Check the NetID. • Change the position of the Bluetooth Repeater Outdoor or install additional Bluetooth Repeater Outdoor devices.
		There is no device with the same NetID within the radio range.	
		The SMA Bluetooth network has not been established. Only masters, e.g. communication products, initiate network establishment.	• Commission a master in the SMA Bluetooth network.
 is flashing and RDY LED is flashing green	 Three LEDs are flashing	The NetID rotary switch is set to position 1 or 0 .	• Set the NetID rotary switch to the NetID of your plant (see Section 7.2).
	 Three LEDs are flashing	The Bluetooth Repeater Outdoor firmware is defective.	• Contact the SMA Service Line.

11 Technical Data

General Data

Width x height x depth	200 mm x 160 mm x 93 mm
Weight with top-hat rail power supply unit	800 g
Weight with Power Modul	740 g
Mounting location	outdoors
Type of mounting	Wall mounting
Status display	LEDs
Degree of protection*	IP54
Certified countries	All EU Member States

* according to IEC 60529

Voltage Supply via Top-Hat Rail Power Supply Unit

Input voltage	100 V ... 240 V AC
Tolerance value for input voltage	± 10%
Frequency of input voltage	47 Hz ... 63 Hz
Typical power consumption	1.8 W
Maximum power consumption	2.5 W
Overvoltage category	II

Voltage Supply via the Power Module

Input voltage	12 V ... 24 V AC/DC
Tolerance value for input voltage	± 20%
Typical power consumption	0.6 W
Maximum power consumption	1.5 W

Environmental Conditions in Operation

Ambient temperature	– 25°C ... +60°C
Relative humidity, non-condensing	4% ... 100%
Altitude above mean sea level (MSL)	0 m ... 2,000 m

Ambient Conditions for Storage/Transport

Ambient temperature	– 40°C ... +70°C
Relative humidity, non-condensing	10% ... 95%
Altitude above mean sea level (MSL)	0 m ... 2,000 m

Communication

Inverter	<i>Bluetooth</i>
Data logger	<i>Bluetooth</i>
Range in open air	≤ 100 m

12 Contact

If you have technical problems concerning our products, please contact the SMA Service Line. We require the following information in order to provide you with the necessary assistance:

- Type, serial number and firmware version of the inverter
- Serial number of the communication product
- Firmware version or software version of the communication product
- Serial number and firmware version of the *Bluetooth* Repeater Outdoor

SMA Solar Technology AG

Sonnenallee 1

34266 Niestetal, Germany

www.SMA.de

SMA Service Line

Inverters: +49 561 9522 1499

Communication: +49 561 9522 2499

Fax: +49 561 9522 4699

E-Mail: ServiceLine@SMA.de

Legal Provisions

The information contained in this document is the property of SMA Solar Technology AG. Publishing its content, either partially or in full, requires the written permission of SMA Solar Technology AG. Any internal company copying of the document for the purposes of evaluating the product or its correct implementation is allowed and does not require permission.

Declaration of Conformity

SMA Solar Technology AG hereby declares that the described device / devices fulfill the essential requirements and other relevant rules of Directive 1999/5/EC. The entire Declaration of Conformity can be found at www.SMA.de.

SMA Factory Warranty

The current warranty conditions come enclosed with your device. These are also available online at www.SMA-Solar.com and can be downloaded and are available on paper from the usual sales channels if required.

Trademarks

All trademarks are recognized even if these are not marked separately. Missing designations do not mean that a product or brand is not a registered trademark.

The *Bluetooth*® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by SMA Solar Technology AG is under licence.

QR Code® is a registered trademark of DENSO WAVE INCORPORATED.

SMA Solar Technology AG

Sonnenallee 1
34266 Niestetal
Germany

Tel. +49 561 9522-0
Fax +49 561 9522-100
www.SMA.de
E-Mail: info@SMA.de

© 2004 to 2012 SMA Solar Technology AG. All rights reserved

SMA Solar Technology

www.SMA-Solar.com

SMA Solar Technology AG

www.SMA.de

SMA Australia Pty. Ltd.

www.SMA-Australia.com.au

SMA Benelux bvba/sprl

www.SMA-Benelux.com

SMA Beijing Commercial Company Ltd.

www.SMA-China.com.cn

SMA Central & Eastern Europe s.r.o.

www.SMA-Czech.com

SMA France S.A.S.

www.SMA-France.com

SMA Hellas AE

www.SMA-Hellas.com

SMA Ibérica Tecnología Solar, S.L.U.

www.SMA-Iberica.com

SMA Solar India Pvt. Ltd.

www.SMA-India.com

SMA Italia S.r.l.

www.SMA-Italia.com

SMA Japan K.K

www.SMA-Japan.com

SMA Technology Korea Co., Ltd.

www.SMA-Korea.com

SMA Middle East LLC

www.SMA-Me.com

SMA Portugal - Niestetal Services Unipessoal Lda

www.SMA-Portugal.com

SMA Solar (Thailand) Co., Ltd.

www.SMA-Thailand.com

SMA Solar UK Ltd.

www.SMA-UK.com

