



Certificate G83/1-1

Engineering Recommendation

Manufacturer:	SMA Solar Technology AG
Address:	Sonnenallee 1
Postal code, place:	34266 Niestetal
Country:	Germany

Test house details:	SMA Solar Technology AG , R&D Department, Niestetal (D)
---------------------	--

Type reference:	Sunny Boy SB 1100LV
	Windy Boy WB 1100LV
Max. AC power:	1100 W
Nominal AC power:	1000 W

The results of the G83/1-1 tests are summarized in this certificate. SMA declares that all devices (with G83 setting) that are shipped to the UK comply with the requirements defined in engineering recommendation G83/1-1. These setting cannot be changed by an installer, user or by any other person without the use of a tool (password protected). The complete documentation can be viewed at SMA (headquarters) after prior announcement.

Test details

- Power quality
- Harmonic current emissions as per BS EN 61000-3-2 A
- Voltage fluctuations and flicker as per BS EN 61000-3-3 A
- DC injection / Power factor
- Under / Over frequency switch off
- Under / Over voltage switch off
- Loss of mains test

SMA Solar Technology AG

Niestetal, 11.02.2010

i. V. Frank Greizer
Vice President T MP

Test results

Power quality

Harmonic current emissions as per BS EN 61000-3-2 A								
Harmonic	2 nd	3 rd	5 th	7 th	9 th	11 th	13 th	15 th ... 39 th
Limit [A]	1.08	2.3	1.14	0.77	0.4	0.33	0.21	0.15 x (15/n)
Test value [A]	0.023	0.015	0.025	0.037	0.032	0.048	0.026	< limit BS EN 61000-3-2 A

Voltage Fluctuations and Flicker				
Harmonic	starting	stopping	running	
Limit	4 %	4 %	$P_{st} = 1.0$	$P_{it} = 0.65$
Test value	1.21 %	1.06 %	0.18	0.17

	DC injection			Power factor		
G83/1-1 Limit	20 mA, tested at three levels			0.95 lag - 0.95 lead at three voltage levels at P_{rated}		
Test level	10 %	55 %	100 %	212 V	230 V	248 V
Test value	4.66 mA	4.05 mA	5.27 mA	0.997	0.997	0.997

Under / Over frequency switch off

Parameter	Under frequency switch off		Over frequency switch off	
	Frequency (Hz)	Time (s)	Frequency (Hz)	Time (s)
G83/1-1 Limit	47 Hz +/- 0.5 %	5 s	50.5 Hz +/- 0.5 %	5 s
Actual setting	49.5 Hz	-	50.5 Hz	-
Trip value	49.51 Hz	< 1 s	50.49 Hz	< 1 s

Under / Over voltage switch off

Parameter	Under voltage switch off		Over voltage switch off	
	Voltage (V)	Time (s)	Voltage (V)	Time (s)
G83/1-1 Limit	207 V	5 s	264 V	5 s
Actual setting	209 V	-	261 V	-
Trip value	208.6 V	< 1 s	260.5 V	< 1 s

Loss of mains test, tested by (a)

Method used	Resonant Circuit as per Annex C		
Output power level	10 % P_{rated}	55 % P_{rated}	100 % P_{rated}
G83/1-1 Limit	(0.5) 5 s	(0.5) 5 s	(0.5) 5 s
Trip setting	-	-	-
Trip value	0.35 s	0.5 s	0.8 s

Reconnection time measurement

	Under / Over voltage	Under / Over frequency	Loss of mains
Minimum value	180 s	180 s	180 s
Actual setting	180 s	180 s	180 s
Recorded value	205 s	208 s	220 s

Fault level contribution

As Photovoltaic SSEGs are inverter connected, they are deemed to automatically comply with regulations and no further tests are required.

Self monitoring – solid state switching

Not applicable as electro-mechanical relays used.