

SMA FUEL SAVE CONTROLLER



User-friendly

- Simple connection to the generator system
- Exchange real-time data via Modbus®

Stable

- Optimal control of solar energy feed-in
- Reverse power protection functionality
- Several optimization and communication functions available

Flexible

- Plant and system parameters are fully configurable
- Modular design accommodates most system setups
- PLC-based modular system with high-quality, industrial-grade components

Scalable


- Supports future system expansion
- Allows for subsequent integration of energy storage systems

SMA FUEL SAVE CONTROLLER

Integrating photovoltaics into fossil-fueled power generation systems

The SMA Fuel Save Controller is a key component in PV diesel hybrid system solutions. As the link between diesel generator, PV system and load, the SMA Fuel Save Controller takes on all demand-based control of PV feed-in depending on the load and generation profiles. Therefore, maximum reliability is guaranteed while fuel costs and CO₂ emissions are reduced. Together with SMA's Sunny Tripower and Sunny Central lines of inverters, the SMA Fuel Save Controller meets comprehensive grid management functions. SMA hybrid systems can be expanded on a modular basis and provide reliable system control through remote monitoring.

Technical data	SMA FUEL SAVE CONTROLLER		
	PV Main Controller Module	Data Acquisition Module	Interface Module
General Data			
Dimensions (W / H / D) in mm (approx.)	600 x 600 x 210	600 x 600 x 210	600 x 600 x 210
Weight (approx.)	30 kg	30 kg	30 kg
Protection rating per IEC 60529	IP 65	IP 65	IP 65
Ambient Conditions			
Operating temperature range	-10 °C ... +50 °C		
Maximum operating altitude	2000 m above mean sea level		
Humidity	5 % ... 95 % (non-condensing)		
Power supply			
Voltage supply (rated)	110 ... 240 VAC (50 ... 60 Hz)		
Power consumption (approx.)	200 W	200 W	200 W
Communication			
Plant communication to supervisory plant control, SCADA and remote monitoring	Modbus/TCP, http, FTP over Ethernet 10 BASE-T and 100 BASE-T(X) Remote monitoring over UMTS/GSM (optional)		
Communication between modules / Maximum cable length	Ethernet over optical fiber through SC connector Ethernet copper based (optional) / 2000 m		
Communication to inverters / Maximum cable length	STP: Speedwire, 10/100 Mbit/s SC: Ethernet 100 BASE-FX and 100 BASE-TX (optional) / STP: 100 m, SC: 2000 m		
Communication protocol to genset controllers	MODBUS/TCP over Ethernet 10 BASE-T and 100 BASE-T(X)		
Other interfaces			
Multi-functional digital inputs (for potential-free contacts, maximum voltage drop @ 10mA: 5V)	8	2	-
Multi-functional digital outputs (potential-free contacts)	4	-	-
Voltage / Current measurement	-	VT (for grid voltages higher than 415 V) / CT (5 A)	-
Visualization & data logging			
Visualization and configuration interface	Web interface for local and remote monitoring		
Data & Event logging	5 second values for 2 days, 5 minute average values for 30 days		
Compatible inverters			
Inverters	Sunny Central CP-XT series, Sunny Tripower (STP 10000TL, STP 12000TL, STP 15000TL, STP 15000TLEE, STP 17000TL, STP 20000TLEE)		
General system design characteristics			
System size (PV system size)	300 kVA ... 6 MVA		
Maximum PV power ratio	60 % of the max. genset capacity (parallel operated)		
Maximum number of handled gensets	5 (no restriction if power limitation is available through supervisory control)		
Type designation	FSC10CONT	FSC10DAQ	FSC10IFM



FSC0US132311 SMA and Sunny Island are registered trademarks of SMA Solar Technology AG. Text and figures comply with the state of the art applicable when printing. Subject to technical changes. We accept no liability for typographical and other errors.