



**SUNNY CENTRAL 500CP XT/630CP XT/
720CP XT/760CP XT/800CP XT/
850CP XT/900CP XT/1000CP XT**

Project name:

Customer:

Address, location of the system:

Inverter serial number

Product version of the inverter

i Content of the maintenance report

In conjunction with the other inverter documentation, the maintenance report assures faultless operation of the inverter and peripheral devices from SMA Solar Technology AG. Maintenance work does not automatically guarantee electrical safety.

The maintenance report contains all necessary maintenance intervals of the inverter as well as the preventive replacement intervals of individual components.

i Storage of the maintenance report

- After maintenance work, keep the maintenance report at hand near the inverter.
- In addition, a copy is to be sent to maintenance.service@sma.de at the latest four weeks after completion of the maintenance work. Enter the serial number of the system on which maintenance was carried out in the subject line.

i Maintenance instructions

- All work must be carried out in accordance with the maintenance manual. All safety information must be observed.

i Regular data backup

Back up and archive the inverter data at regular intervals. This can be done by remote query or during routine maintenance work.

No.	Appendix

1 Checklist

No.	Section	Maintenance work	Interval	Date completed
1.	5.2	Reading off error messages and warnings	1 month* depending on the system size	
2.	6.4.1.1	Checking the DC switchgear	24 months	
3.	6.4.1.2	Checking the AC disconnection unit	24 months	
4.	6.4.1.3	Check the fans	24 months	
5.	6.4.1.4	Checking the heating element and the hygrostat	24 months	
6.	6.4.12	Cleaning the heating element with low-temperature range option	24 months	
7.	6.4.13	Checking the heating elements of the low-temperature range option	24 months	
8.	6.4.16	Checking the function of the UPS	24 months	
9.	6.4.2.1	Perform the visual inspection	24 months	
10.	6.4.2.2	Analyzing the temperature indicators	24 months	
11.	6.4.2.3	Cleaning the ventilation plate	24 months*	
12.	6.4.2.4	Analyzing the temperature indicators	24 months	
13.	6.4.2.5	Clean the air duct, ventilation grids and air intake.	24 months*	
14.	6.4.2.6	Clean the interior	24 months	
15.	6.4.2.7	Checking the door seals	24 months	
16.	6.4.2.8	Checking the latches, door stops and hinges	24 months	
17.	6.4.2.9	Checking the inverter surface	24 months	
18.	6.4.2.10	Checking the fuses/disconnection blades	24 months	
19.	6.4.2.11	Checking the bolted connections	24 months	
20.	6.4.2.12	Check the labels	24 months	

* The maintenance interval may need to be reduced depending on the location or ambient conditions.

2 Preventive Replacement Intervals

No.	Section	Maintenance work	Interval	Date completed
1.	6.3	Replacing the 24 V power supply units	Every 10 years	
2.	6.3	Replacing the 24 V buffer modules	Every 10 years	
3.	6.3	Exterior key switch, front element and label	Every 10 years	
4.	6.3	Replacing the fan of the AC disconnection unit	Every 10 years	
5.	6.3	Replacing the inverter bridge fans	Every 12 years	
6.	6.3	Replacing the interior fan	Every 12 years	
7.	6.3	Surge arrester	If tripped	
8.	6.3	GFDI / ABB high-performance circuit breaker	After 1000 trippings due to short circuit or after 7000 switching cycles	
9.	6.3	Remote Switch Unit of the GFDI	After 7000 switching cycles	
10.	6.3	Key switch	If badly worn	
11.	6.3	Label	If illegible, defective or missing	

Your signature confirms that the work listed above has been carried out.

Customer or contractor company*	Last name, first name*	Date	Signature

* in block letters